查询RCFD1-1950BP5供应商

Dielectric Ceramic Filters and Duplexers

RCFand RDX Series



Applications

- Satellite Receivers-Down Converters
- Global Positioning Systems
- Wireless LAN Equipment
- Cellular and Cordless Phones

Features

- Wide Frequency Range of 600 to 2500 MHz
- High Q Resonator
- Excellent Temperature Stability and Attenuation
- Low Insertion Loss
- Custom Designs for Application Specific Products

Specifications

2 Pole Bandpass Filter

Part Number	Center Frequency	Bandwidth	Insertion Loss	Ripple (Max)	V.S.W.R (Max)	Attenuation (Min)
RCFA1-836BP2	836.5 MHz	F_0±12.5 MHz	2.2 dB	0.8 dB	2	5 dB at Fo±32.5 MHz
RCFA1-881BP2	881.5 MHz					
RCFA1-841BP2	841.0 MHz	F_0±2.0 MHz	2.5 dB	0.3 dB	2	22 dB at Fo±70 MHz
RCFA1-866BP2	866.0 MHz					
RCFA1-948BP2	948.0 MHz	F_0±4.0 MHz	2.5 dB	0.5 dB	2	
RCFA1-902BP2	902.5 MHz	F_0±12.5 MHz	2.2 dB	0.8 dB	2	6 dB at Fo±32.5 MHz
RCFA1-947BP2	947.5 MHz					
RCFA1-915BP2	915.0 MHz	F_0±13.0 MHz	2.3 dB	1.0 dB	2.5	18 dB at Fo±80 MHz
RCFA1-1575BP2	1575.5 MHz	F_0±1.0 MHz	3.0 dB	0.5 dB	2	18 dB at Fo±50 MHz
RCFA1-1890BP2	1890.0 MHz	F_0±10.0 MHz	1.8 dB	0.5 dB	2	16 dB at Fo±160 MHz

Outline Drawing



RCFA Package

Typical Applications for RCFA Series

E-Amps
CT-2
GSM
ISM915

Raltron Electronics Corporation 10651 NW 19th St. Miami, Florida 33172 U.S.A.
Tel: 305-593-6033 Fax: 305-594-3973 e-mail: sales@raltron.com Internet: http://www.raltron.com

Specifications

3 Pole Bandpass Filter

Part Number	Center Frequency	Bandwidth	Insertion Loss (Max)	Ripple (Max)	V.S.W.R (Max)	Attenuation (Min)
RCFB1-815BP3	815.0 MHz	F_0±10.0 MHz	2.8 dB	0.8 dB	2	36 dB @ Fo±80 MHz
RCFB1-860BP3	860.0 MHz					
RCFB1-836BP3	836.5 MHz	F_0±12.5 MHz	3.0 dB	1.0 dB	2	12 dB @ Fo±32.5 MHz
RCFB1-881BP3	881.5 Mhz					
RCFB1-841BP3	841.0 MHz	F_0±2.0 MHz	3.0 dB	0.3 dB	2	44 dB @ Fo±75 MHz
RCFB1-866BP3	866.0 MHz					
RCFB1-948BP3	948.0 MHz	F_0±4.0 MHz	3.0 dB	0.5 dB	2	32 dB @ Fo±50 MHz

Outline Drawings



RCFB1 Package

Applications for RCFB1

LMR
E-Amps
CT-2

Part Number	Center Frequency	Bandwidth	Insertion Loss (Max)	Ripple (Max)	V.S.W.R (Max)	Attenuation (Min)
RCFB2-888BP3	888.5 MHz	F_0±16.5 MHz	3.0 dB	1.3 dB	2	7 dB @ Fo±28.5 MHz
RCFB2-933BP3	933.5 MHz					
RCFB2-902BP3	902.5 MHz	F_0±12.5 MHz	2.6 dB	1.0 dB	2	12 dB @ Fo±32.5 MHz
RCFB2-947BP3	947.5 MHz					
RCFB2-915BP3	915.5 MHz	F_0±13.0 MHz	3.0 dB	1.0 dB	2	12 dB @ Fo±32.5 MHz
RCFB2-897BP3	897.5 MHz	F_0±17.5 MHz	3.0 dB	1.3 dB	2	6 dB @ Fo±28.5 MHz
RCFB2-942BP3	942.5 MHz					



RCFB2 Package

Applications for RCFB2

GSM
E-TACS
ISM915
E-GSM

Raltron Electronics Corporation 10651 NW 19th St. Miami, Florida 33172 U.S.A.
Tel: 305-593-6033 Fax: 305-594-3973 e-mail: sales@raltron.com Internet: http://www.raltron.com

Specifications

4 Pole Bandpass Filter

Part Number	Center Frequency	Bandwidth	Insertion Loss (Max)	Ripple (Max)	V.S.W.R (Max)	Attenuation (Min)
RCFC1-1930BP4	1930.0 MHz	F_0±10.0 MHz	4.5 dB	0.8 dB	2	40 dB @ Fo±70 MHz
RCFC1-2120BP4	2120.0 MHz					
RCFC1-2315BP4	2315.0 MHz	F_0±15.0 MHz	4.5 dB	1.0 dB	1.8	40 dB @ Fo±90 MHz
RCFC1-2385BP4	2385.0 MHz					

Outline Drawings



RCFC1 Package

Applications for RCFC1

IMT-2000
WLL

Part Number	Center Frequency	Bandwidth	Insertion Loss (Max)	Ripple (Max)	V.S.W.R (Max)	Attenuation (Min)
RCFC2-813BP4	813.0 MHz	F_0±5 MHz	3.5 dB	0.5 dB	2	30 dB @ Fo±40 MHz
RCFC2-813BP4	836.5 MHz	F_0±12.5 MHz	3.0 dB	0.8 dB	2	20 dB @ Fo±32.5 MHz
RCFC2-813BP4	881.5 MHz					



RCFC2 Package

Applications for RCFC2

TRS
AMPS

Raltron Electronics Corporation 10651 NW 19th St. Miami, Florida 33172 U.S.A.
Tel: 305-593-6033 Fax: 305-594-3973 e-mail: sales@raltron.com Internet: http://www.raltron.com

Specifications

5 Pole Bandpass Filter

Part Number	Center Frequency	Bandwidth	Insertion Loss (Max)	Ripple (Max)	V.S.W.R (Max)	Attenuation (Min)
RCFD1-1310BP5	1310.0 MHz	F_0±17.5 MHz	4.1 dB	1.6 dB	2	12 dB @ Fo±28 MHz
RCFD1-1950BP5	1950.0 MHz	F_0±30.0 MHz	3.0 dB	1.0 dB	1.5	40 dB @ 2070 MHz
RCFD1-2140BP5	2140.0 MHz					40 dB @ 2260 MHz
RCFD1-2800BP5	2800.0 MHz	F_0±1000 MHz	3.0 dB	1.6 dB	2	60 dB @ Fo±1000 MHz
RCFD1-836BP5	836.5 MHz	F_0±12.5 MHz	3.0 dB	1.0 dB	2	28 dB @ Fo±32.5 MHz
RCFD1-881BP5	881.5 MHz					
RCFD1-808BP5	808.0 MHz	F_0±5.0 MHz	4.5 dB	1.0 dB	2	50 dB @ Fo±45 MHz
RCFD1-852BP5	852.0 MHz					
RCFD1-1690BP5	1690.0 MHz	F_0±25.0 MHz	4.0 dB	1.0 dB	2	50 dB @ Fo±140 MHz
RCFD1-1972BP5	1972.0 MHz	F_0±2.5 MHz	5.0 dB	0.5 dB	2	25 dB @ Fo±32.5 MHz

Outline Drawings



RCFD1 Package



RCFD2 Package

Applications for RCFD1/D2

RADIO LINK
IMT- 2000
LAN
AMPS
TRS

Specifations for the RCFD1 package are also available for the RCFD2 Package.
Other specifations are available in these packages.

Raltron Electronics Corporation 10651 NW 19th St. Miami, Florida 33172 U.S.A.
Tel: 305-593-6033 Fax: 305-594-3973 e-mail: sales@raltron.com Internet: http://www.raltron.com

Specifications

6 Pole Bandpass Filter

Part Number	Center Frequency	Bandwidth	Insertion Loss (Max)	Ripple (Max)	V.S.W.R (Max)	Attenuation (Min)
RCFE1-2332BP6	1030.0 MHz	F_0±4.5 MHz	5.0 dB	0.8 dB	2	45 dB @ Fo±25.0 MHz
RCFE1-1030BP6	2332.5 MHz	F_0±27.5 MHz	3.0 dB	1.0 dB	2	23 dB @ Fo±57.5 MHz

Outline Drawings



RCFE1 Package

Applications for RCFE1/E2

Satellite Link
IMT- 2000



RCFE2 Package

Specifations for the RCFE1 package are also available for the RCFE2 Package.
Other specifations are available in these packages.

Raltron Electronics Corporation 10651 NW 19th St. Miami, Florida 33172 U.S.A.
Tel: 305-593-6033 Fax: 305-594-3973 e-mail: sales@raltron.com Internet: http://www.raltron.com

Specifications

8 Pole Bandpass Filter

Part Number	Center Frequency	Bandwidth	Insertion Loss (Max)	Ripple (Max)	V.S.W.R (Max)	Attenuation (Min)
RCFF1-645BP8	645.0 MHz	F_0±5.0 MHz	5.0 dB	0.5 dB	2	70 dB @ Fo±70 MHz
RCFF1-675BP8	675.0 MHz					
RCFF1-735BP8	735.0 MHz					
RCFF1-765BP8	765.0 MHz					
RCFF1-795BP8	795.0 MHz					
RCFF1-836BP8	836.5 MHz	F_0±12.5 MHz	5.5 dB	2.0 dB	2	70 dB @ Fo±42.5 MHz
RCFF1-847BP8	847.14 MHz	F_0±1.85 MHz	20.0 dB	2.2 dB	2	20 dB @ Fo±5 MHz
RCFF1-892BP8	892.14 MHz					
RCFF1-902BP8	902.5 MHz	F_0±12.5 MHz	5.5 dB	1.5 dB	2	60 dB @ Fo±44.5 MHz
RCFF1-911BP8	911.5 MHz		15.0 dB	3.5 dB	2	70 dB

Outline Drawing



TOLERANCE: ±0.3 mm

RCFF1 Package

Other specifications are available in the RCFF1 package.

Specifications

Duplexers

Part Number		Center Frequency	Bandwidth	Insertion Loss	Ripple (Max)	V.S.W.R (Max)	Attenuation (Min)
RDXA-R2180-T1690A	Tx	1690 MHz	Fo±32.5 MHz	1.5 dB	0.5 dB	1.5	50 dB at 1718 MHz
	Rx	2180 MHz		2.0 dB	0.5 dB	1.5	50 dB at 2152 MHz
RDXA-R1855-T1765A	Tx	1765 Mhz	Fo±15.0 MHz	1.7 dB	1.0 dB	1.5	42 dB at Fr±15 MHz
	Rx	1855 MHz		2.5 dB	1.0 dB	1.5	43 dB at Fr±15 MHz
RDXA-R2385-T2315A	Tx	2315 MHz	Fo±15.0 MHz	1.5 dB	1.0 dB	1.5	45 dB at Fr±15 MHz
	Rx	2385 MHz		2.5 dB	1.0 dB	1.5	50 dB at Fr±15 MHz
RDXA-R947-T902A	Tx	902.5 MHz	Fo±12.5 MHz	2.5 dB	0.8 dB	1.5	48 dB at Fr±12.5 MHz
	Rx	947.5 MHz		3.0 dB	0.8 dB	1.5	48 dB at Fr±12.5 MHz
RDXA-R2140-T1950A	Tx	1950 MHz	Fo±30.0 MHz	2.0 dB	0.5 dB	1.5	50 dB at Fr±15 MHz
	Rx	2140 MHz		2.0 dB	1.0 dB	1.5	50 dB at Fr±15 MHz
RDXA-R858-T813A	Tx	813 MHz	Fo±5.0 MHz	2.0 dB	0.8 dB	1.5	50 dB at Fr±.05 MHz
	Rx	858 MHz		2.0 dB	0.8 dB	1.5	50 dB at Fr±5.0 MHz
RDXA-R881-T836A	Tx	836.5 MHz	Fo±12.5 MHz	2.0 dB	0.8 dB	1.5	50 dB at Fr±12.5 MHz
	Rx	881.5 MHz		2.3 dB	0.8 dB	1.5	50 dB at Fr±15 MHz
RDXA-R1855-T1765A	Tx	1765 MHz	Fo±15.0 MHz	2.0 dB	0.8 dB	1.5	55 dB at Fr±15 MHz
	Rx	1855 MHz		2.0 dB	0.8 dB	1.5	55 dB at Fr±15 MHz

Outline Drawing



RDXA Package

Other specifations are available in the RDXA package.
Also other duplexer package types are available.

Raltron Electronics Corporation 10651 NW 19th St. Miami, Florida 33172 U.S.A.
Tel: 305-593-6033 Fax: 305-594-3973 e-mail: sales@raltron.com Internet: http://www.raltron.com